Residential/Light Commercial Generator Accessories

KOHLER. Power Systems

Maintenance Kits











Note: Illustration does not show all available kits

Applicable Models

• 6 - 60 kW Kohler® Residential and Light Commercial Generators

Description

Keep your Kohler® generator running at peak performance with one of our maintenance kits featuring genuine Kohler® oil and parts. Each kit includes everything you need to perform periodic maintenance on your generator, including the spark plugs, air cleaner element, oil filter, and pre-measured oil required for your generator.

Regular use of Kohler generator maintenance kits can:

- Promote peak performance
- Ensure ease of starting

- Extend generator life
- Prevent costly repairs

Refer to the generator set operation manual for recommended maintenance intervals for your model. Keep proper maintenance records and use quality Kohler® parts and materials to help keep your system running smoothly for years to come.

KOHLER CO., Kohler, Wisconsin 53044 USA Phone 920-457-4441, Fax 920-459-1646 For the nearest sales and service outlet in the US and Canada, phone 1-800-544-2444 KOHLERPower.com Kohler Power Systems Asia Pacific Headquarters 7 Jurong Pier Road Singapore 619159 Phone (65) 6264-6422, Fax (65) 6264-6455

Generator Set Model	8.5RES	6VSG, 12RES(L) 14RES(A)(AL)(L)	8RESV(L)	10/12RESV(L)	17/18RES(L) 20RES(A)(AL)(B) (C)(CL)(D)(L)	15RES(A)/R(E)YG 30RES(A)/R(E)YG
Engine	CH640	CH740	SV620	KT725	CH1000	1.6L
Maintenance Kit Part Number	GM62345-SKP1-QS	GM62346-SKP1-QS	GM90365-SKP1-QS	GM90366-SKP1-QS	GM62347-SKP1-QS	GM62348-SKP1-QS
Kit Package Weight, kg (lbs.)	2.8 (6.15)	2.9 (6.3)	2.8 (6.15)	2.9 (6.3)	4.0 (8.9)	5.1 (11.2)
Kit Package Dimensions, mm (in.)	254 x 280 x 203 (10 x 11 x 8)	229 x 229 x 330 (9 x 9 x 13)	229 x 229 x 330 (9 x 9 x 13)	254 x 330 x 229 (10 x 13 x 9)	254 x 330 x 229 (10 x 13 x 9)	229 x 229 x 330 (9 x 9 x 13)
Kit Components,	qty.	•		•		
Air filter	1 *	1 *	1	1	1	1
Oil, synthetic	2	2	2	2	3	4
Oil filter	1	1	1	1	1	1
Spark plugs	2	2	1	2	2	4

Generator Set Model	24RCL	30RCL 38RCLB	38RCL	48RCL	60RCL
Engine	KG2204, 2.2L	KG2204T, 2.2L Turbo	4.3L	5.0L	5.7L
Maintenance Kit Part Number	GM93396-SKP1-QS	GM100209-SKP1-QS	GM86771-SKP1-QS	GM83718-SKP1-QS	GM89979-SKP1-QS
Kit Package Weight, kg (lbs.)	5.1 (11.2)	5.1 (11.2)	6.4 (14.1)	6.4 (14.1)	6.8 (15)
Kit Package Dimensions, mm (in.)	229 x 229 x 330 (9 x 9 x 13)	229 x 229 x 330 (9 x 9 x 13)	381 x 254 x 229 (15 x 10 x 9)	381 x 254 x 229 (15 x 10 x 9)	381 x 254 x 229 (15 x 10 x 9)
Kit Components,	qty.		•		
Air filter	1	1	1 *	1 *	1
Oil	4	4	5	5	5
Oil filter	1	1	1	1	1
Spark plugs	4	4	6	8	8
* Includes pre-clea					

IST			

Availability is subject to change without notice. Kohler Co. reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever. Contact your local Kohler® generator distributor for availability.

© 2013, 2014, 2015, 2016 by Kohler Co. All rights reserved.